



ENERGY 1000 START



Overview

ENERGY 1000 START

cod. 829008

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230V-400V



CE MARKING



EAC CERTIFICATION



REMOTE CONTROLS

Technical data

CODE	CODE 829008	A_{EFF}	EFFECTIVE CHARGING CURRENT 100 A		ADJUSTMENT POSITIONS 5
V_{3PH}	THREE PHASE MAINS VOLTAGE 230 / 400 V	A_{EN}	RATED CHARGE CURR. EN60335-2-29 80 A		DIMENSIONS 38 x 56 x 88,5 cm
F	MAINS FREQUENCY 50 / 60 Hz	A_{IV/C}	START CURRENT 1V/C EN60335-2-29 640 A		WEIGHT 45 kg
P_{CHARGE}	CHARGE POWER 2,5 KW	A_{START MAX}	MAX STARTING CURRENT 1000 A	BAR CODE	EAN CODE 800489736539 8
P_{START}	START POWER 20 KW	C_{MIN}	MIN. RATED REFERENCE CAPACITY 20 Ah		PIECES/PALLET 6 pz/pallet
	CHARGING VOLTAGE 12 / 24 V	C_{MAX}	MAX RATED REFERENCE CAPACITY 1600/ 800 A		PIECES/PALLET - B 4 pz/pallet-B



ENERGY 1000 START

Included Accessories

CABLE 25 MMQ 2,5 M - 123456

CABLE 25 MMQ 3 M - 123467

REMOTE CONTROL 6 M - 123993

POSITIVE CLAMP (+) - 712025

WORK CLAMP - 712026