



UT120B Pocket-sized Residential Multimeter

UT120 series multimeters are designed for DIYers and electronics engineers to troubleshoot electronics systems development and electronics circuits. It is a simple and portable multimeter for every electronics engineer.

Applications:

It can used in troubleshoot electronics systems development and electronics circuits.

Specifications	Range	UT120B
DC voltage (V)	600V	$\pm(0.8\%+1)$
AC voltage (V)	600V	$\pm(1.2\%+3)$
Resistance (Ω)	40M Ω	$\pm(1\%+2)$
Capacitance (F)	100 μ F	$\pm(4\%+3)$
Frequency (Hz)	100kHz	$\pm(0.5\%+3)$
Features		
Display count		4000
Auto range		√
Duty cycle	0.1%~99.9%	√
Diode		√
Auto power off	Around 30 minutes	√
Continuity buzzer		√
Low battery indication	$\leq 2.4V$	√
Data hold		√
Relative mode		√
Input impedance for DCV	Around 10M Ω	√
General Characteristics		
Power	3V battery (CR2032)	
Display	43mm x 22mm	
Product color	Red and grey	
Product net weight	76g	
Product size	110mm x 58.2mm x 10.8mm	
Standard accessories	Battery, carrying case	
Standard individual packing	Blister, English manual	
Standard quantity per carton	100pcs	

Standard carton measurement	750mm x 275mm x 490mm (0.1CBM per export carton)
Standard carton gross weight	20kg