

Digital Resistance Meter

ZMDRM200m to ZMDRM2M



| | |
|-----------------------------|---|
| Make | ZEAL |
| Model | ZMDRM200m to ZMDRM2M |
| Power | 230V AC, 50Hz ± 10% |
| Measurements Range | 200mΩ, 2Ω, 20Ω, 200Ω, 2000Ω, 20kΩ, 200kΩ, 2MΩ |
| Test current | 1μA to 1A as per measurement range |
| Open circuit voltage | 5V or as per customer requirement |
| Meter | 3½ digits |
| Typical Accuracy | 1.5% ±3 digits |

- Digital Resistance meter are very useful for measuring dc winding resistance of motors, transformers etc. Meter available in wide range of resistance. They are highly reliable in industrial noisy atmosphere.