

sanwa®

TOKYO JAPAN

VOLTAGE DETECTOR

KD2



APPLICATIONS AND FEATURES

This instrument is a AC voltage detector, which tests for defective grounds and energized circuits.

- Beeping and LED lighting upon detection
- Switchable to measure cable or bare wireon)

SPECIFICATIONS

	Measuring range
Measurement	Voltage Detection
Voltage range	AC80V - 600V, 50/60Hz
Compatible conductor	Cable or bare wire
Withstand voltage	AC2000V for 1 minute
Pilot light Indicator	The Red LED lights up and the buzzer sounds when the cable or wire is live Beep : Over 50dB from 50cm away LED : 8000Lx
Operating temperature	-10°C~45°C
Battery	Alkaline button cell LR44(1.5V) x 2
Battery life	Approx. 6 hours
Size / Mass	H133 x W19 x D19.5mm / Approx. 17g

A battery for monitoring has been installed prior to shipment from the factory. It may be discharged before the expiration of the described battery life. This battery is used to check the functions and performance of the product. Specifications and external appearance of the product described above may be revised for modification without prior notice.

sanwa®

SANWA ELECTRIC INSTRUMENT CO., LTD.

Dempa Bldg, 4-4 Sotokanda 2-Chome, Chiyoda-Ku, Tokyo 101-0021 Japan
Tel:+81-3-3251-0941 Fax:+81-3-3256-9740

www.sanwa-meter.co.jp

Distributed by