



LEADER 220 START



Overview

LEADER 220 START

cod. 807539

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage, and starting all types of petrol-driven vehicles.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- display of charging and starting current
- protection against overloads and polarity reversal.



1 PH 230V



CE MARKING



EAC CERTIFICATION

Technical data

CODE	CODE 807539	A_{EFF}	EFFECTIVE CHARGING CURRENT 30 A		ADJUSTMENT POSITIONS 2
V_{1PH}	SINGLE PHASE MAINS VOLTAGE 230 V	A_{EN}	RATED CHARGE CURR. EN60335-2-29 20 A		DIMENSIONS 22,5 x 29 x 20,5 cm
F	MAINS FREQUENCY 50 / 60 Hz	A_{1V/C}	START CURRENT 1V/C EN60335-2-29 120 A		WEIGHT 9 kg
P_{CHARGE}	CHARGE POWER 0,8 KW	A_{START MAX}	MAX STARTING CURRENT 180 A	BAR CODE	EAN CODE 800489788516 2
P_{START}	START POWER 3,6 KW	C_{MIN}	MIN. RATED REFERENCE CAPACITY 30 Ah		PIECES/PALLET 56 pz/pallet
	CHARGING VOLTAGE 12 / 24 V	C_{MAX}	MAX RATED REFERENCE CAPACITY 400 A		PIECES/PALLET - B 42 pz/pallet-B

Included Accessories

CABLE 6 MMQ 2 M AND WORK CLAMP - 123569

CABLE 6MMQ 2 M POSITIVE CLAMP - 123588