



LEADER 400 START



Overview

LEADER 400 START

cod. 807551

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage, and starting all types of petrol-driven and diesel-driven vehicles, up to 70 hp.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- display of charging and starting current
- protection against overloads and polarity reversal.



1 PH 230V



CE MARKING



EAC CERTIFICATION

Technical data

CODE	CODE 807551	A_{EFF}	EFFECTIVE CHARGING CURRENT 45 A		ADJUSTMENT POSITIONS 3
V_{1PH}	SINGLE PHASE MAINS VOLTAGE 230 V	A_{EN}	RATED CHARGE CURR. EN60335-2-29 31 A		DIMENSIONS 26,5 x 34,5 x 23 cm
F	MAINS FREQUENCY 50 / 60 Hz	A_{1V/C}	START CURRENT 1V/C EN60335-2-29 180 A		WEIGHT 10,9 kg
P_{CHARGE}	CHARGE POWER 1 KW	A_{START MAX}	MAX STARTING CURRENT 300 A	BAR CODE	EAN CODE 800489764804 0
P_{START}	START POWER 6,4 KW	C_{MIN}	MIN. RATED REFERENCE CAPACITY 20 Ah		PIECES/PALLET 27 pz/pallet
	CHARGING VOLTAGE 12 / 24 V	C_{MAX}	MAX RATED REFERENCE CAPACITY 700 A		PIECES/PALLET - B 36 pz/pallet-B

Included Accessories

CABLE 10 MMQ 2 M - 123425



COLORADO 150R POSITIVE CLAMP 150A - 712002



LEADER 400 START



COLORADO 150B WORK CLAMP 150A - 712001