



## DT-9967/9967T/99

### 69

9969 is a Professional digital multimeter with 50000 counts resolution and a 0.06% basic DC accuracy within the reach of more customers.

9967/9967T series are the new 6600 counts multimeters. They are a combination of precision, easy-to-use, safety and reliability.

9967T has True RMS AC Voltage, Current readings, MAX-MIN recording, as well as Frequency and

Capacitance readings.

All inputs are protected by EN 610101-1 CATIV 600V/CATIII 1000V.



<b>Features</b>			
	<b>9967</b>	<b>9967T</b>	<b>9969</b>
<b>Digital display counts</b>	<b>6600</b>	<b>6600</b>	<b>50,000</b>
<b>50,000 counts high resolution (0.001mV, 0.01µA, 0.01Ω)</b>			*
<b>True RMS measurement</b>		*	*
<b>1000V input protection on all ranges</b>	*	*	*
<b>Data Hold/ MAX/MIN /Relative function</b>	*	*	*
<b>Auto Power Off</b>	*	*	*
<b>Analog bargraph &amp; segment</b>	*	*	*
<b>NCV Function</b>	*	*	

<b>Specifications</b>					
<b>Function</b>	<b>Max. Range</b>	<b>Basic Accuracy</b>	<b>9967</b>	<b>9967T</b>	<b>9969</b>
<b>Voltage DC</b>	<b>1000 V</b>	<b>±0.5%</b>	*	*	<b>±0.06%</b>
<b>Voltage AC</b>	<b>1000V</b>	<b>±0.8%</b>	*	*	<b>±1.0%</b>
<b>Current DC</b>	<b>10A</b>	<b>±1.2%</b>	*	*	<b>±1.0%</b>
<b>Current AC</b>	<b>10A</b>	<b>±1.8%</b>	*	*	<b>±1.5%</b>
<b>Resistance</b>	<b>60MΩ</b>	<b>±0.8%</b>	*	*	<b>±0.3%</b>
<b>Duty Cycle</b>	<b>99.9%</b>	<b>±1.2%</b>	*	*	<b>±1.2%</b>
<b>Frequency</b>	<b>10MHz</b>	<b>±1.5%</b>	*	*	<b>±0.1%</b>
<b>Capacitance</b>	<b>100 µ F/60mF</b>	<b>±3.0%</b>	*	*	<b>±3.5%</b>
<b>Temperature</b>	<b>760°C/1400°F</b>	<b>±3.0%</b>	*	*	<b>±1.0%</b>
<b>Diode Check</b>			*	*	*
<b>Continuity Test</b>			*	*	*

**Accessories: Test leads, 9V battery.Type K temperature probe and gift box.**