











# DT-9915/9915T/99 16/9917/9917T/99 18/9918T

# Professional Digital Multimeters

The seven models of the new 9915,9915T, 9916, 9917,9917T, 9918 and 9918T series are the new 4000 counts multimeters. They set the standard with a combination of precision, features, easy-to-use, safety and reliability. 9915T/9917T/9918T have True RMS AC Voltage, Current readings, as well as Frequency and Capacitance ranges.

Safety Conformance
EN61010-1 CAT IV 600V, CAT III 1000V
1000V input protection on all ranges
10A/1000V & 0.5A/1000V fuses
protection on current ranges



Features	DT-9915/9915T	DT-9916	DT-9917/9917T	DT-9918/9918T
Digital display counts	4000	4000	4000	4000
True RMS measurement	DT-9915T		DT-9917T	DT-9918T
Safety design	*	*	*	*
Relative zero	*	*	*	
Data Hold	*	*	*	*
MAX/MIN recording mode				
Auto Power Off	*	*	*	*
Peak capture mode				*
Wide capacitance range		20mF		*
Current DC/AC 40µA		*		
Analog bargraph/segment				*

Size(HxWxD): 182mm x 82mm x 55mm Weight: 360g

Specifications								
Function	Max. Range	Basic Accuracy	DT-9915/9915	DT-9916	DT-9917/9917	DT-9918/991		
			Т	סופפיוט	Т	8T		
Voltage DC	1000 V	±0.5%	*	*	*	*		
Voltage AC	1000 V	±0.8%	*	*	*	*		
Current DC	10A	±1.2%	*	*	*	*		
Current AC	10A	±1.8%	*	*	*	*		
Resistance	40ΜΩ	±0.8%	*	*	*	*		
Duty Cycle	99.90%	±1.2%	*	*	*			
Frequency	10MHz	±1.5%	*	*	*			
Capacitance	200 μ F/40mF	±3.0%	200μF	20mF	200μF	40mF		
Temperatur e	760°C/1400 °F	±3.0%			*	*		
Diode Check		*	*	*	*			
Continuity Test		*	*	*	*			

### **Applications**



IP67 dust and water proof

True RMS (9915T/9917T/9918T)

## **Professional Digital Multimeters**

The seven models of the new 9915,9915T, 9916, 9917,9917T, 9918 and 9918T series are the new 4000 counts multimeters. They set the standard with a combination of precision, features, easy-to-use, safety and reliability. 9915T/9917T/9918T have True RMS AC Voltage, Current readings, as well as Frequency and Capacitance ranges.

#### **Safety Conformance**

- •EN61010-1 CAT IV 600V, CAT III 1000V
- 1000V input protection on all ranges
- •10A/1000V & 0.5A/1000V fuses
- protection on current ranges

#### **Accessories:**

Test leads and 9V battery,

Type K temperature probe (9917/9918/9917T/9918T), gift box with carrying case.