



### UT133B Digital Multimeter

UT133A/B is a palm size multimeter adopting intellectual ADC chip. It provides overload alarm as well as electricity protection. It is a professional device designed for electric industry.

## Applications:

### Electric industry

Specifications	Range	UT133B
DC voltage (V)	600mV/6000mV/60V/600V	$\pm(0.5\%+3)$
AC voltage (V)	600V	$\pm(1.2\%+3)$
DC current (A)	600uA/60mA/600mA/10A	$\pm(1\%+2)$
Resistance ( $\Omega$ )	600 $\Omega$ /6000 $\Omega$ /60k $\Omega$ /600k $\Omega$ /60M $\Omega$	$\pm(0.8\%+2)$
Capacitance (F)	9.999nF/99.99nF/999.9nF/9.999 $\mu$ F/99.99 $\mu$ F/999.9 $\mu$ F/9.999mF	$\pm(4\%+5)$
Features		
Display count		6000
Range selection		Manual
Diode		√
Continuity buzzer		√
Battery test	Tests 1.5V and 9V batteries and displays 'good', 'low', 'bad' status	√
NCV		√
LCD backlight		√
Test probe holder		√
Data hold		√
Low battery indication		√
Overload indication		√
General Characteristics		
Power	1.5V battery (R03) x 2	
Display	56.8mm x 36.1mm	
Product color	Red and grey	
Product net weight	255g (with batteries)	
Product size	155mm x 76.5mm x 49mm	
Standard accessories	Manual, test leads	

Standard individual packing	Gift box, English manual
Standard quantity per carton	350mm x 335mm x 318mm
Standard carton measurement	30pcs
Standard carton gross weight	12.5kg