



DT-10/12/16/16A

Pocket Digital Multimeter

4000 counts, 8 functions including DCV, ACV, DCA, ACA, Resistance, Continuity, Diode test with Data Hold, Low impedance and non-contact ACV detection.

Large high contrast 4000 counts LCD display with Analog bargraph

Auto Power off



EMC & LVD
EN: 61326
EN: 61010-1,
EN: 61010-02-031



Relative, and Data Hold

Built-in storage compartment for integrated test leads


Over-range and low battery indication

Size (H x W x D): 126mm x 59mm x 32mm

Weight: 124g

Specifications	DT-10	
Function	Max. Range	Accuracy
Voltage DC	600V	±(1.3%±2d)
Voltage AC	600V	±(2.3%±5d)
Current DC	200mA	±(1.5%±2d)
	4000µA/6000µA	±(2.5%±5d)
Current AC	200mA	±(2.5%±5d)
	4000µA/6000µA	±(2.5%±5d)
Resistance	40MΩ	±(2.0%±2d)
Continuity	Audible threshold <50Ω	
Diode Test	Test Current 0.6mA	

Applications



Pocket Digital Multimeter

- 4000 counts, 8 functions including DCV, ACV, DCA, ACA, Resistance, Continuity, Diode test with Data Hold, Low impedance and non-contact
- ACV detection.
- Large high contrast 4000 counts LCD display with Analog bargraph
- Auto Power off
- Relative, and Data Hold
- Built-in storage compartment for integrated test leads
- Over-range and low battery indication

Built-in Non-Contact Voltage Detector automatically detects a live wire when the red LED is lit

Oversized high contrast 4000/6000 counts LCD Display

Rubber Protection

Accessories: Test leads, Wallet style case and one 1.5V L44 button battery.