



### UT603 Inductance Capacitance Meter

UT600 series digital inductance capacitance meters are used to test resistors, capacitors and inductors. They can also be used to measure transistor parameters.

Applications:

It can be used to check electronic components in electronic labs, production lines, maintenance facilities and schools.

Specifications	Range	UT603
Resistance ( $\Omega$ )	200 $\Omega$ /2k $\Omega$ /20k $\Omega$ /200k $\Omega$ /2M $\Omega$ /20M $\Omega$	$\pm(0.8\%+1)$
Capacitance (F)	2nF/20nF/200nF/2uF/20uF/200uF/600uF	$\pm(1\%+5)$
Inductance (H)	2mH/20mH/200mH/2H/20H	$\pm(2\%+8)$
Features		
Display count		2000
Manual range		√
Diode		√
Transistor		√
Continuity buzzer		√
Low battery indication		√
General Characteristics		
Power	9V battery (6F22)	
Display	61mm x 32 mm	
Product color	Red and grey	
Product net weight	UT601/UT602: 310g, UT603: 312g	
Product size	172mm x 83mm x 38mm	
Standard accessories	Battery, test leads with alligator clips, holster	
Standard individual packing	Gift box, English manual	
Standard quantity per carton	20pcs	
Standard carton measurement	450mm x 330mm x 340mm (0.099CBM per standard carton)	
Standard carton gross weight	9.6kg	