



LA-101

3 in 1 Stud/Metal/AC Voltage Finder

LA-101 uses electronic signals to locate the edges of studs, joists or live AC wires through drywall or other common building materials. Depth detection selected by activation button for 1/2 inch, 1 inch and 1½ inch. Once LA-101 displays red LED and sounds an audible tone.



Specifications	
	Range
Wood or Metal Studs	0~ 1½ " (38mm)
Live AC Wires	0~ 2 " (50mm)
Wood	±1/8 " (3mm)
Metal	±1/4 " (6mm)
Operating Temp	0°C~40°C
Surface Temp	-20°C~60°C
Power Source	9V

Size(HxWxD): 145mm x 60mm x 28mm

Weight: 150g

Accessories: 9V battery, gift box with carrying case.