



DT-380/380B/381/382 /383

Compact AC, AC/DC Autoranging Clamp Meters

The 380 series clamp meters offer all the features you need to fit the way you work. The small bodies and jaws fit perfectly in your hand and into tight places.



Features					
	380	380B	381	382	383
Current measurement	AC	AC	AC	AC/DC	AC/DC
LCD display counts	2000	2000	4000	2000	4000
Data Hold	*	*	*	*	*
REL(Zero) Function		MAX		*	*
Auto Power Off	*	*	*	*	*
Low battery indication	*	*	*	*	*
1.2"(30mm) Jaw opening	*	*	*	*	*
NCV Detection	*		*	*	*
Flashlight	*		*	*	*

Size(HxWxD): 230mm x 82mm x 40mm

Weight: 230g

Specifications							
Function	Max. Range	Basic Accuracy	380	380B	381	382	383
Voltage DC	600V	$\pm(0.5\%+1d)$	*	*	*	*	*
Voltage AC	600V	$\pm(1.5\%+2d)$	*	*	*	*	*
Current DC	400A	$\pm(2.0\%+5d)$				200A	*
Current AC	400A	$\pm(2.5\%+4d)$	*	*	*	200A	*
Resistance	40M Ω	$\pm(3.0\%+5d)$	20M Ω	*	*	20M Ω	*
Temperature	1000°C/1832°F	$\pm(3.0\%+3d)$	*	*	*	*	*
Capacitance	100uF	$\pm(2.5\%+5d)$		*	*		*
Frequency	10MHz	$\pm(1.2\%+2d)$		*	10kHz		10kHz
Continuity check	Buzzer sounds at 50 Ω						
Diode test	Test current 0.3mA						

Accessories:

Test leads, gift box with carrying case, Temperature probe and Two"AAA"1.5V batteries.