







UT230B-US Power Socket

UT230B series power sockets can be inserted to monitor the operating status (voltage, current, time, and power consumption, and more) of electrical appliances. Alarm will go off and display 'OL' when errors are found. The socket jacks are designed to meet the needs of different regions with proper certifications. UT230B series are ideal tools for maintaining equipment

power consumption and a good tool for managing energy saving in homes, offices, schools, and other places.

Specifications	Range	Best Accuracy	
Model		UT230B-US	
Voltage	100.0V~260.0V	±1%	
Current	0A~16.00A	±1%	
Frequency	45Hz~65Hz	V	
Power	0~3680W	±1%	
Power Factor	0~1.00	±2%	
Energy Consumption	0~9999kWh	±1%	
Feature			
Unit Price of Electricity	0.00~99.99 (\$/kWh)	√	
Accumulative Time	0 minute~9999 days	√	
Accumulative Charge	0~9999\$	√	
CO ₂ Display	0~9999kg	√	
Power Consumption	<0.4W	√	
Overload Indication	>16A	√	
General Characteristics	'		
Power	3.0 V Button Battery	3.0 V Button Battery	
Product Color	White	White	
Product Net Weight	140g	140g	
Product Size	130mm×65mm×59mm	130mm×65mm×59mm	
Standard Accessories	Batteries	Batteries	
Standard Individual Packing	Blister, English Manual	Blister, English Manual	
Standard Quantity Per Carton	48pcs	48pcs	
Standard Carton Measurement	445mm X405mm X 395mm (0.071	445mm X405mm X 395mm (0.071 CBM Per Standard Carton)	
Standard Carton Gross Weight	11.7kg	11.7kg	